

**IN THE CLAIMS:**

This listing of claims will replace all prior versions and listings of claims in the application:

**Listing of Claims:**

1 (Original). A method of operating an equalizer which is provided in a digital communications receiver to reduce symbol decoding errors therein and which has a feed forward digital filter defined by a plurality of feed forward coefficients and a feedback digital filter defined by a plurality of feedback coefficients, comprising:

determining initial values for a subset of said coefficients without determining initial values for the remainder of said coefficients;  
thereafter, in response to the initial values of the subset of said coefficients, determining subsequent values for the subset of said coefficients and also for the remainder of said coefficients; and  
based on the subsequent values of said coefficients, using the equalizer to decode symbols that have arrived at the receiver in a digital transmission burst.

2 (Original). The method of Claim 1, wherein said step of determining initial values includes using a first coefficient determination algorithm to determine the initial values, and wherein said step of determining subsequent values includes determining the subsequent values according to a second coefficient determination algorithm that differs from said first coefficient determination algorithm.

3 (Original) The method of Claim 2, wherein the first coefficient determination algorithm is more computationally complex than the second coefficient determination algorithm.

4 (Original). The method of Claim 3, wherein the first coefficient determination algorithm includes one of a Least Squares algorithm and a Weighted Least Squares algorithm.

5 (Original). The method of Claim 4, wherein the second coefficient determination algorithm includes a Least Mean Squares algorithm.

6 (Original). The method of Claim 3, wherein the second coefficient determination algorithm includes a Least Mean Squares algorithm.

7 (Original). The method of Claim 1, wherein said step of determining initial values includes determining initial values for a subset of the feed forward coefficients without determining initial values for the remainder of the feed forward coefficients.

8 (Original). The method of Claim 7, wherein said step of determining initial values includes determining initial values for the feedback coefficients in response to the initial values of the subset of feed forward coefficients.

9 (Original). The method of Claim 8, wherein said step of determining subsequent values includes determining the subsequent values in response to the initial values of the subset of feed forward coefficients and the initial values of the feedback coefficients.

10 (Original). An equalization apparatus for reducing symbol decoding errors in a digital communications receiver, comprising:

- a feed forward digital filter having an input for receiving digital transmission bursts, said feed forward digital filter defined by a plurality of feed forward coefficients;

- a decision element having an input coupled to said feed forward digital filter for deciding what symbols are included in the received digital transmission bursts, said decision element having an output for providing a signal indicative of the decided symbols;

- a feedback digital filter having an input coupled to said output of said decision element for filtering said signal indicative of the decided symbols, said feedback digital filter having an output for providing a filtered version of said signal, said output of said feedback digital filter coupled to said input of said decision element, said feedback digital filter defined by a plurality of feedback coefficients; and

a coefficient determiner coupled to said feed forward filter and said feedback filter for determining initial values for a subset of said coefficients without determining initial values for the remainder of said coefficients, and for thereafter determining subsequent values for the subset of said coefficients and also for the remainder of said coefficients in response to the initial values of the subset of said coefficients, said coefficient determiner having an output coupled to said feed forward digital filter and said feedback digital filter for first outputting said initial coefficient values to said filters and for thereafter outputting said subsequent coefficient values to said filters.

11 (Original). The apparatus of Claim 10 wherein said coefficient determiner includes a coefficient initializer selectively connectable to said feed forward digital filter and said feedback digital filter for using a first coefficient determination algorithm to determine said initial values for said subset of coefficients, said coefficient determiner further including a subsequent coefficient calculator for determining said subsequent coefficient values according to a second coefficient determination algorithm that differs from said first coefficient determination algorithm.

12 (Original). The apparatus of Claim 11, wherein said first coefficient determination algorithm is more computationally complex than said second coefficient determination algorithm.

13 (Original). The apparatus of Claim 12, wherein said first coefficient determination algorithm includes one of a Least Squares algorithm and a Weighted Least Squares algorithm.

14 (Original). The apparatus of Claim 13, wherein said second coefficient determination algorithm includes a Least Mean Squares algorithm.

15 (Original). The apparatus of Claim 12, wherein said second coefficient determination algorithm includes a Least Mean Squares algorithm.

16 (Original). The apparatus of Claim 11, wherein said coefficient initializer includes a feed forward coefficient calculator for determining initial values for a subset of the feed forward coefficients without determining initial values for the remainder of the feed forward coefficients.

17 (Original). The apparatus of Claim 16, wherein said coefficient initializer includes a feedback coefficient calculator coupled to said feed forward coefficient calculator for determining initial values for the feedback coefficients in response to the initial values of the subset of feed forward coefficients.

18 (Original). The apparatus of Claim 17, wherein said subsequent coefficient calculator is responsive to the initial values of the subset of feed forward coefficients and the initial values of the feedback coefficients for determining said subsequent coefficient values.

19 (Original). The apparatus of Claim 10, wherein said feedback digital filter includes a finite impulse response filter and said feed forward digital filter includes a finite impulse response filter.

20. Canceled.

21. Canceled.

22. Canceled.

23. Canceled

24. Canceled.

25. Canceled.

26 (Previously Amended). A method of reducing symbol decoding errors in a digital communication system comprising:

determining initial values for a subset of a plurality of feed forward and feedback coefficients without determining initial values for the remainder of said coefficients;

in response to the initial values of the subset of said coefficients, determining subsequent values for the subset of coefficients and the remainder of the plurality of feed forward and feedback coefficients; and  
decoding symbols using the subsequent values.

27 (Previously Added). The method of claim 26, wherein  
the feed forward coefficients define a feed forward digital filter; and  
the feedback coefficients define a feedback digital filter.

28 (Previously Added). The method of claim 26, wherein the subset includes feed forward coefficients, feedback coefficients, or a combination of feed forward and feedback coefficients.

29 (Previously Amended). An equalization apparatus for reducing symbol decoding errors in a digital communications system, comprising:  
a feed forward digital filter defined by a plurality of feed forward coefficients;  
a feedback digital filter coupled to the feed forward digital filter and defined by a plurality of feedback coefficients; and  
a coefficient determiner coupled to said feed forward filter and said feedback filter and configured to  
determine initial values for a subset of the plurality of feed forward and feedback coefficients without determining initial values for the remainder of said coefficients; and  
in response to the initial values of the subset of said coefficients, determine subsequent values for the subset of coefficients and the remainder of the plurality of feed forward and feedback coefficients.

30 (Previously Added). The apparatus of claim 29, further comprising:  
a decision element coupled between the feed forward digital filter and the feedback  
digital filter, the decision element configured to  
decide what symbols are included in a digital transmission bursts; and  
generate a signal indicative of the decided symbols.

31 (Previously Added). The apparatus of Claim 29 wherein the coefficient  
determiner comprises:  
a coefficient initializer selectively connectable to the feed forward digital filter and the  
feedback digital filter for using a first coefficient determination algorithm to  
determine the initial values for the subset of coefficients; and  
a subsequent coefficient calculator for determining the subsequent coefficient values  
according to a second coefficient determination algorithm that differs from the  
first coefficient determination algorithm.

**This Page is Inserted by IFW Indexing and Scanning  
Operations and is not part of the Official Record**

## **BEST AVAILABLE IMAGES**

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

☐ **BLACK BORDERS**

☐ **IMAGE CUT OFF AT TOP, BOTTOM OR SIDES**

☒ **FADED TEXT OR DRAWING**

☐ **BLURRED OR ILLEGIBLE TEXT OR DRAWING**

☐ **SKEWED/SLANTED IMAGES**

☐ **COLOR OR BLACK AND WHITE PHOTOGRAPHS**

☐ **GRAY SCALE DOCUMENTS**

☒ **LINES OR MARKS ON ORIGINAL DOCUMENT**

☐ **REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY**

☐ **OTHER:** \_\_\_\_\_

**IMAGES ARE BEST AVAILABLE COPY.**

**As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.**